



NEW FEATURES ⊕ | UPDATED FUNCTIONALITY ⬆ | JUNE 2020

## Version 202 Update

Version 202 (6/1/20) firmware is now available on Dealer Admin ([dealer.securecomwireless.com](https://dealer.securecomwireless.com)) or for download at [DMP.com/Dealer\\_Direct](https://DMP.com/Dealer_Direct).

Effective June 29th, 2020, all XR Series Panels are being manufactured with Version 202 firmware.

## Panel Features

### Card+Pin By Area

Previously, when Card+Pin was enabled on a User Profile, the user would have to use a credential and their pin in every area assigned to the profile. With XR Version 202, Card+Pin has been made an area option as well, which allows certain areas to be designated to require the presentation of a credential and the users pin number. To use this feature, Card+Pin must be set to Yes in Area Information and in the User Profile.

### New Private Door Option

With XR Series Version 202, there is a new programming option in **Device Setup** for private doors. When a door is designated as a private door, it will not be assigned to an access area. The door can then be added to a profile, with up to four private doors per profile.

### Removal of Messaging Setup

With XR Series Version 202, Messaging Setup has been removed from panel programming and is no longer supported. For your customers that would like to continue to receive SMS messages for panel events, they will need to:

1. Sign in to [VirtualKeypad.com](https://VirtualKeypad.com).
2. Select **Notifications** tab. Here you can select existing notifications or create new notifications.
3. Select the **Recipients** tab. This will let you choose whether to receive notifications through push, text, or email.

### 734N/734N-POE Local Event Storage

XR Series Version 202 supports local event storage in 734N/734N-POE Version 105 firmware. For more information, refer to the 734N/734N-POE Version 105 TU:

- [734N/734N-POE Version 105 Feature Update \(TU-1153\)](#)

## Panel Enhancements

### 263LTE-FIRSTNET Support

XR Series Version 202 supports the upcoming 263LTE-FIRSTNET Cellular Communicator that operates on the AT&T FirstNet broadband network.

### PIR Walk Test Remote Command

With XR Series 202, you can now initiate a PIR Walk Test remotely from Dealer Admin or the Tech APP. This test works similarly to the Wireless Walk Test and Standard Walk Test. The PIR needs to be tripped in order to test properly. The PIR LED will flash each time motion is detected for up to 30 minutes.

### Easy Wi-Fi Password Programming

If the panel detects that the Wi-Fi password is incorrect, the keypad will display a message telling the user that they need to change the password. The keypad then walks the user through the steps for changing the password.

### Improved Weather Accuracy

When the panel receives a weather update, it will compare the zip code in the weather string against the zip code it has in programming. If the zip codes match, the panel will update the weather. If the zip codes do not match, the panel will ignore the weather string. This ensures the panel is always providing the user with accurate weather information.

## Supporting Software Updates

- **Dealer Admin Version 2.46** - Supports Card+Pin By Area, Private Door, and the PIR Walk Test.
- **Tech APP Version 2.8.0** - Supports Private Door, FirstNet Cellular Network, and the PIR Walk Test.
- **Virtual Keypad Website Version 2.25.0** - Supports Private Door feature.

## Obtaining the New Firmware

XR Series firmware updates are available, free of charge, on Dealer Admin ([dealer.securecomwireless.com](http://dealer.securecomwireless.com)) or [DMP.com/Dealer\\_Direct](http://DMP.com/Dealer_Direct).