



XTLplus

WIRELESS BURGLARY CONTROL PANEL



PLACE YOUR LOGO HERE

FEATURES

- ▶ 900 MHz Two-Way Wireless™ and Z-Wave® built on board
- ▶ Designed for fast, reliable wireless installations
- ▶ Cellular, Wi-Fi and network communication to monitoring center
- ▶ 99 two-way, 900 MHz wireless with up to 48 pre-named zones
- ▶ Supports seven fully functional two-way wireless keypads
- ▶ Supports up to eight two-way wireless key fobs or outputs
- ▶ Supports eight fully functional two-way wireless sirens
- ▶ Remote panel updates via cellular or network
- ▶ Auto keypad pairing for 9800 Series wireless keypads

- ▶ Small plastic enclosure can be easily mounted or located anywhere and can be customized with your logo light pipe
- ▶ Uses cellular services from SecureCom Wireless® with a modular cellular communicator and external antenna
- ▶ Remote control via Virtual Keypad™ or VirtualKeypad.com
- ▶ EASYconnect™ connection for the Virtual Keypad app when used with a Wi-Fi or network connection
- ▶ All/Perimeter, Home/Sleep/Away or six Areas
- ▶ 99 four-digit user codes with authority levels
- ▶ 200-event memory
- ▶ Auto WPS on Wi-Fi models
- ▶ Supports 140 Z-Wave devices
- ▶ Arm only, ambush code and temporary user code options
- ▶ Built-in standby battery
- ▶ Built-in programming from any keypad
- ▶ Built-in access control with the 1134 Wireless Access Control Module
- ▶ Selectable automatic arming and disarming
- ▶ Open/Close schedules with Closing Check
- ▶ Late to Open/Early to Close and Traffic Count features for retail applications
- ▶ Attrition Detection™ monitors system for arming activity
- ▶ Programmable user inactivity monitor watches for on-site activity
- ▶ Remote program/download with Remote Link™, Dealer Admin™ or Tech APP™
- ▶ 16-character zone, user and area names



DEALER MANAGEMENT FEATURES

ONBOARD OPTIONS: CELLULAR, WI-FI AND NETWORK

The XTLplus can be configured to use dual communication with Wi-Fi or network as primary and cellular as backup.

DIRECT DATA TRANSMISSION

The cellular communicators or network/Wi-Fi data network transmit messages directly from the panel to the monitoring center. All of the messages being sent by the control panel are received directly by a DMP monitoring center receiver. There is no retransmission or reinterpretation of the information. Direct reporting means faster response, with no concerns about signals not being properly relayed or intermediate communication links failing.

RECEIVER 1 AND 2 OPERATION

Select one or two receivers for messages regarding alarms, supervisory/trouble, opening/closing and test reports. Send all messages to both receivers or identify one receiver for alarms and the second for reports or trouble messages to alert only the proper responder.

ONBOARD WIRELESS

The XTLplus control panel includes a high-gain wireless receiver on board supporting the 1100 Series™ wireless devices. These 900 MHz frequency-hopping, spread-spectrum devices feature two-way communication for superior operation, supervision and battery life. Two-way communication minimizes repetitive signaling and helps to quickly identify missing transmitters.

With 99 wireless zones, the transmitter options are more than sufficient for most installs. The XTLplus' unique wireless features include motion detectors that are configurable over the air. Also included are eight key fob zones or eight wireless outputs including arm/alarm LED, wireless sirens and wireless relays. All of these features make the XTLplus a perfect choice for residential or small commercial applications.

HOME/SLEEP/AWAY

For residential applications, the homeowner can press one button to select each of three separate arming options. They can select Home to arm the perimeter of the home but allow for movement within the house. Select Sleep to arm the perimeter and only specified areas inside their home, leaving sensors near bedrooms disarmed. Selecting Away fully arms all elements of the system.

ALL/PERIMETER

In business applications, system users can quickly select All to completely arm the system as they leave the facility for the day. They also have the option to select Perimeter, arming all exterior sensors at doors and windows but disarming all interior sensors so employees can move freely around the facility.

CROSS ZONING

This powerful, false-alarm-reduction feature allows zones to be cross-zoned and report alarms only when two or more zones fault within a programmable time of 4 to 250 seconds. If one zone trips, only a zone fault report is sent to the monitoring center.

POWERING THE PANEL

The panel is powered by a small 12-volt plug-in power supply. Standby battery is included.

1100T WIRELESS TRANSLATOR

The 1100T is the industry's only wireless translator listed and approved for life safety. Plus, it makes it easy to take over DSC, Interlogix, Honeywell 5800 and 2 GIG Series systems, all without replacing existing transmitters and sensors. To accommodate the maximum number of supported sensors on the XTLtouch, one 1100T can learn in 99 zones. It communicates to a DMP panel using the panel's built-in wireless receiver. This eliminates wiring and allows you to place the translator anywhere regardless of where the control panel is. With this one device, you can upgrade customers systems' to DMP quality, with software management tools, as well as online and app convenience and functionality without increasing installation costs.

FULLY SUPERVISED

You're kept fully informed of system status. The unit sends full reporting messages including zones, areas and users, with all names and details included. Full supervision ensures that the cellular or network communication path is intact and functional.

ONE-STOP CELLULAR

SecureCom Wireless provides a reliable wireless solution for the XTLplus transmission of alarm signals to the monitoring center receiver. See SecureComWireless.com for more information.

EASYconnect TECHNOLOGY

EASYconnect enables the control panel to establish an outbound connection to SecureCom over Wi-Fi or network. This allows for an effortless installation of network panels without any customer router programming, providing extremely quick app connection times.

FAST PROGRAMMING

Fast Programming lets your installers power through most programming data inputs and lets them get the job done faster. When the panel programming defaults are acceptable for installation, and only basic programming options are needed, Fast Programming allows the technician to quickly enter information without navigating all of the programming menus.

- ▶ Receiver IP
- ▶ Weather Zip Code
- ▶ System (Area, A/P or H/S/A)
- ▶ Hours from GMT
- ▶ Wireless Siren Serial Number
- ▶ Zone Information

All standard programming options are still available in the programming menu from the keypad, Tech APP, Dealer Admin or Remote Link.

AUTO WPS

The XTLplus control panel provides the ability to connect to a Wi-Fi network easily with the Auto WPS feature. Once the XTLplus is powered on, users press the WPS button on the router to connect the XTLplus to the Wi-Fi network automatically. If Auto WPS is unavailable, the list of available Wi-Fi networks will pop up on the 9800 keypad to manually select your preferred network.

BUILT-IN PROGRAMMER

An internal English-text programmer enables technicians to easily program and test the panel from any keypad. A lockout code restricts access to only authorized persons.

ATTRITION DETECTION PROMPTS YOU TO CALL YOUR CUSTOMER

The exclusive DMP Attrition Detection feature gives you advance warning that a customer may be preparing to cancel their monitoring contract. With this feature activated, you will receive a notification if there has been no system activity for the number of days you select.

WIRELESS KEYPAD ASSOCIATION

This is a great time-saver for installers. Any keypad not associated with another panel is accepted and assigned to the first open keypad address available. Keypads are automatically assigned based on the order in which they are detected. A maximum of seven keypads may be associated with a panel.

REMOTE PROGRAMMING

Remotely program panels using the Tech APP, DMP Remote Link software or the Dealer Admin site. Upload panel programming, make the necessary programming change and then download the revised programming into the panel.

FIELD PANEL UPDATES

The 401 USB Flash Module allows you to easily field update firmware for panels that would otherwise require the use of a computer and a 399 Programming Harness.

END USER MANAGEMENT FEATURES

SIMPLE ARMING

XTLplus provides multiple arming configurations: Area arming with six separate areas; All/Perimeter arming with perimeter and interior areas; or Home/Sleep/Away arming with perimeter, interior and bedroom areas. Users can arm the perimeter and interior at night while leaving the bedroom area disarmed.

RETAIL APPLICATIONS

The Late to Open/Early to Close feature sends a message to the monitoring center if the facility isn't opened on time or it closes before the scheduled time. The Traffic Count sends a daily tally of trips for the specified zone.

Z-WAVE SUPPORT

Add up to 140 Z-Wave devices with the 738Zplus module for mobile control of lights, locks and thermostats. Up to 20 Favorites allow users to program multiple devices to respond to a single command or panel events like arming and disarming. Z-Wave devices can be controlled with the 9800 Series Graphic Touchscreen Keypad or Virtual Keypad.

VIRTUAL KEYPAD APP

This app provides users with the ability to access a number of system functions remotely via a cellular or Wi-Fi connection. As a dealer, the app provides the opportunity to use your company logo. The Virtual Keypad app offers the following features:

- ▶ System Arming/Disarming
- ▶ All/Perimeter, Home/Sleep/Away or Multi-Area Operation
- ▶ Panel Output Status and Control
- ▶ Control of Z-Wave Thermostats, Lights, Locks and Garage Door
- ▶ Favorites (control multiple Z-Wave devices with a single button)
- ▶ Actions allows users to associate Favorites to activate specific events
- ▶ Program a picture (user takes) of a room with hotspots that controls the Z-Wave devices
- ▶ Real-time weather for your local zip code
- ▶ Sensor activity zone setting
- ▶ View live video and clips from cameras
- ▶ Geofencing
- ▶ User code management includes the ability to add, delete or edit users from the system
- ▶ Push notifications and view history of alarm events, arming/disarming and troubles by other users on the system
- ▶ Control doors (1134), lock and unlock from Virtual Keypad

VIRTUALKEYPAD.COM

Users can access their security system via Internet connection on a tablet or computer. Customers log in to VirtualKeypad.com with their login and system user code.

WIRELESS KEYPADS

The 9000 Series and 9800 Series wireless keypads are fully functioning, supervised keypads that provide installation flexibility. The keypads also include a built-in proximity reader for codeless arming and disarming.

FALSE ALARM FEATURES

Providing a way to reduce false alarms, Cancel/Verify™ and False Alarm Question prompt users to validate whether an alarm has occurred after entering their code. In a Home/Sleep/Away or All/Perimeter system, the user can either press Verify or Yes to manually confirm a valid burglar alarm, and an alarm is then sent to the monitoring center.

KEYPAD SHORTCUT KEYS

Keypad shortcut keys simplify operation and allow the user to more quickly arm, check in, monitor, exit or reset the system. One-button arming creates the simplest keypad operation available. Use the one-button shortcut keys for common functions, or use the ATM-style menu for advanced functions.

USER CODES

Program up to 99 codes. Assign a Standard or Master Authority level to control each user's level of access to the system with scheduled and limited users.

EVENT MEMORY

The XTLplus panel logs up to 200 user and system events that you can view at any time through a keypad User Menu option. The Display Events feature allows users to view stored events such as openings and closings, zone events, user code changes and supervisory events.

ZONE INACTIVITY

With Zone Activity Hours, you can easily monitor a person living alone. If there is no activity at the premises within the programmed number of hours, the system transmits an SMS message to your cell phone. The monitoring center also receives an alert. It's a valuable feature for customers looking after aging adults.

ZONE AUDIT

The Zone Audit feature allows programming the panel to send an alert when the sensor fails to trip within the specified number of days. This feature helps identify potential sensor problems, including sensors deactivated to bypass faults or blocked sensors.

SUPPORT FOR WIRELESS DOOR CONTROL

The 1134 Wireless Access Control Module allows customers to take advantage of the panel's powerful built-in access control capabilities. In hard-to-wire locations, such as a gate or warehouse entrance, this eliminates the need for costly wire runs or trenching and provides the ease and flexibility to add access control in nearly any environment. For customers who want to add an even hardened layer of security, all DMP wireless devices and receivers offer full support of 128-bit encryption capabilities.

XTL+N

The XTLplus Series also offers a hardwired network option. The XTL+N is designed with hardwired network connection and an optional cellular module for backup communications. For customers who have trouble with weak Wi-Fi signal, the XTL+N is an ideal solution by removing that potential instability. The XTL+N provides that convenience and ensures customers always have reliable communications to their security company.

COMPATIBILITY REFERENCE SHEET

Keypads

9060-W	Wireless Keypad
9060-W/699	Wireless Keypad with Deskstand
9063-W	Wireless Keypad with Prox Reader
9063-W/699	Wireless Keypad with Prox Reader and Deskstand
9862USB-B	Wireless Graphic Touchscreen Keypad
9862USB-W	Wireless Graphic Touchscreen Keypad
9862-W	Wireless Graphic Touchscreen Keypad
9862-B	Wireless Graphic Touchscreen Keypad

CELLULAR COMMUNICATORS

265LTE-V	LTE Verizon
265LTE-A	LTE AT&T

Monitoring Center Receivers

SCS-IR	Security Control Receiver
SCS-VR	Software Receiver

Dealer Management

Remote Link Programming Software
Dealer Admin

End User Management

VirtualKeypad.com
Virtual Keypad

**DMP Wireless**

1100R	Repeater
1101	Universal Transmitter Internal and External Contacts
1102	Universal Transmitter External Contact
1103	Universal Transmitter Internal and External Contacts
1106	Universal Transmitter Internal and External Contacts
1107	Micro Window Transmitter
1108	Doorbell Module
1114	Four-Zone Expander
1115	Temperature Sensor and Flood Detector
1115-W/T280R	Temp Sensor/Flood Detector and Temp Sensor Probe
1115-W/470PB	Temp Sensor/Flood Detector and Water Sensor Probe
1116	Relay Output
1117	LED Annunciator
1119	Door Sounder
1122	PIR
1126R	360 Ceiling Mount PIR
1127C	Wall Mount Curtain PIR
1127W	Wall Mount Wide Angle PIR
1128	Glassbreak Detector
1131	Recessed Contact

1134	Access Control Module
1135	Siren
1136	Remote Chime
1139	Bill Trap
1141	Wall Button
1142	Two-Button Hold-up Transmitter
1142BC	Two-Button Belt Clip Hold-up Transmitter
1144-4	Four-Button Key Fob
1144-2	Two-Button Key Fob
1144-1	One-Button Key Fob
1144-D	Dual-Button Key Fob
1148	Personal Pendant
1154	Four-Zone Input Module
1158	Eight-Zone Input Module
1164NS	Smoke Detector with No Sounder
1164	Smoke Detector with Synchronized Sounder
1166	Smoke Ring
1168	Smoke/CO/Low Temp Detector
1183-135F	Heat Detector, Fixed
1183-135R	Heat Detector, Rate of Rise
1184	Carbon Monoxide Detector

Encrypted Wireless Models

1101E	Universal Transmitter
1103E	Commercial Universal Transmitter
1106E	Universal Transmitter
1135E	Siren
1142E	Two Button Hold Up Transmitter
1144-4E	Four-Button Key Fob
1144-2E	Two-Button Key Fob
1144-1E	One-Button Key Fob

Z-Wave

Z-14319	In Wall Toggle Switch
Z-46561	Z-Wave Toggle Style Auxiliary Switch
Z-46565	Z-Wave In-Wall Dimmer Switch
Z-52190	Z-Wave LED Light Bulb
Z-98880-004	Z-Wave Door Deadbolt, Satin Nickel
Z-98880-005	Z-Wave Door Deadbolt, Venetian Bronze
Z-98880-006	Z-Wave Door Deadbolt, Polished Brass
Z-99100-STAND	Demo Deadbolt Desk Stand
Z-GD00Z	Z-Wave Garage Door Controller
Z-PD300EMZ5-1	Z-Wave Smart Light Control Module with Dimmer
Z-PS15EMZ5-1	Z-Wave Smart Appliance Control Module
Z-TBZ500	Z-Wave Thermostat

System Specifications**Primary Power:**

12 VDC (Model 372-500-W)

Secondary Power:

3.8 VDC LION Polymer Battery

(Model XTL+BAT800)

XTL+BAT800/8 replacement 8 pk

XTL+BAT3500/8 replacement 8 pk

Dimensions:

5.5" W × 3.75" H × 1" D

Ordering info

XTL+N	XTLplus with Network
XTL+W	XTLplus with Wi-Fi
XTL+WZ	XTLplus with Wi-Fi and Z-Wave
XTL+Z	XTLplus with Z-Wave

Certifications

FCC Wireless Receiver and Z-Wave Approvals

FCC ID: CCKPC0181

IC: 5251A-PC0181

FCC Wi-Fi Network Approvals

FCC ID: VW4-ATWINC1500

IC: 20266-WINC1500PB

Intertek (ETL) Listed

- ▶ ANSI/UL 1023 Household Burglar
- ▶ ANSI/UL 1610 Central Station Burglar
- ▶ ANSI/UL 985 Household Fire

800-641-4282 | DMP.com

2500 N. Partnership Blvd, Springfield, MO 65803

Designed, engineered & manufactured in

Springfield, MO using U.S. & Global Components

LIMITED WARRANTY: DMP warrants that the products manufactured by DMP and described herein shall be free from defects of manufacture, labeling, and packaging for a period of three (3) years from the invoice date to the original Buyer, provided that representative samples of the defective products are returned to DMP for inspection...To read the full DMP Limited Warranty, go to DMP.com/Warranty or check the DMP Price List or Catalog.