



PowerCom **FIRE**™



FEATURES

- ▶ Network communication for all signals is free
- ▶ No need to resubmit battery calculations when upgrading an existing system
- ▶ Provides dual path monitoring center communication for any burglary or commercial fire panel
- ▶ Fully supervised universal alarm communication over LTE and network
- ▶ Communicates with DMP SCS-1R and SCS-VR Receivers
- ▶ 4-2/SIA
- ▶ Program your own account number to easily work around locked panels
- ▶ AT&T or Verizon networks
- ▶ External SMA antenna
- ▶ Use Contact ID dialer capture
- ▶ Two output terminals with multiple output options
- ▶ Ships with its own power supply and 24-hour backup battery



WORKS WITH MOST PANELS

If the existing panel supports Contact ID, it's a candidate for upgrading with PowerCom Fire communicators. There are no issues with lockout codes. Simply add the PowerCom Fire unit to the existing installation and program in your own account number.

FIRE COMMUNICATION

The PowerCom Fire offers both network and cellular fire communication. Either one works on any fire control panel via Contact ID captures. Both meet NFPA 72 standard for single communication technology.

FIRE PANEL TAKEOVER

PowerCom Fire provides two tip and ring terminals to easily take over existing fire panels with two phone lines.

COMMUNICATION FAILURE MONITORING

The phone line voltage on the second tip and ring will drop when the PowerCom Fire is in a communication failure state. This triggers the host panel to announce and display a communication failure.

FULLY SUPERVISED COMMUNICATION

PowerCom Fire allows alarm messages to be communicated to an SCS-1R or SCS-VR Receiver over network or Verizon or AT&T LTE networks. Network communications for all signals is free on all DMP products.

REMOTE UPDATES

The PowerCom accepts software updates using Dealer Admin™. This makes it easy to perform the flash update remotely any time new communicator feature updates release.

REMOTE PROGRAMMING

Programming over network or cell via Dealer Admin™ includes zone information and monitoring center communications.

TWO OUTPUTS

Use outputs to connect to an existing panel for control of that panel via the Virtual Keypad™ app.

EASY UPGRADE FOR DIALER-ONLY PANELS

Older dial-up panels have new life with the addition of network or cellular communication. Earn customer loyalty by extending the life of their existing panels and add modern panel features at the same time.

ADD VIRTUAL KEYPAD APP

Enable the Virtual Keypad app on your customers' existing panels for a minimal additional cost. Brand DMP's Virtual Keypad app with your organization's logo and contact information to provide a daily reminder of your services. The Virtual Keypad app will allow your customers to view events monitored by their system.

NEVER RESUBMIT BATTERY CALCULATIONS AGAIN

When you're upgrading to the PowerCom on an existing fire system, forget about wasting time and money resubmitting battery calculations. Instead, you've got everything you need in a self-powered packaged solution that meets UL, CSFM, NFPA, FCC and FDNY compliance standards.

The PowerCom Fire communicator ships with a transformer and 24-hour backup battery. Whether your customers use network, AT&T or Verizon LTE, this communicator has all the power it needs without drawing from the panel.

When you order the new PowerCom Fire communicator, it comes in a small red enclosure with additional backbox, making this an ideal way to easily upgrade existing fire panels. It's also a great way to replace older, more expensive communications options.

Ordering Information

PowerComF-V	Universal Fire Alarm Communicator with Hardwired Network Primary and LTE Backup (Verizon)
PowerComF-A	Universal Fire Alarm Communicator with Hardwired Network Primary and LTE Backup (AT&T)

Accessories

381-2	18" Coax Extension
381-12	12' Coax Extension
381-25	25' Coax Extension
383P	Cellular Antenna
386	Wall Mount Antenna Bracket
387-2	2 dB Attack Enclosure Antenna
387-4	4' SMA to N Extension Cable
387-8	8' SMA to N Extension Cable
387-25	SMA TO N CABLE, 25FT, LMR195
387-50	SMA TO N CABLE, 50FT, LMR195
388-1	3 dB Fiberglass Antenna w/bracket
388-2	2 dB Attack Enclosure Antenna
388-3	3 dB MEG Antenna
ESS01	Plug-In Transformer Enclosure
ESS02	Transformer Enclosure

Specifications

Primary Power	12 Volt Power Supply Included 12-24VDC Compatible
Current Draw at 12 VDC	
Standby	75 mA
Alarm	280mA when also charging the battery

Dimensions and Color

Housing Color	Red
Dimensions	
Housing	5.5"W x 3.75"H x 1"D
Backbox	6.39"W x 4.73"H x 1.57"D

Certifications

Cellular	
FCC Part 15:	XMR201707BG96 XMR201910BG95M3
IC:	10224A-201709BG96 10224A-2019BG95M3
Underwriters Laboratories (UL) Listed	
PowerComF	
ANSI/UL 864 Fire Protective Signaling Systems, 10th Edition	
California State Fire Marshal (CSFM)	
FCC Part 15	
National Fire Protection Association (NFPA)	
New York City (FDNY)	

For additional information, go to DMP.com/Resources/Compliance-Notes.



800-641-4282 | DMP.com | 2500 N. Partnership Blvd, Springfield, MO 65803

Designed, engineered & manufactured in Springfield, MO using U.S. & global components.

LIMITED WARRANTY: DMP warrants that the products manufactured by DMP shall be free from defects of manufacture, labeling, and packaging for a period of three (3) years from the invoice date to the original Buyer, provided that representative samples of the defective products are returned to DMP for inspection. To read the full DMP Limited Warranty, go to DMP.com/Warranty or check the DMP Price List or Catalog.

Any third-party trademarks referenced herein are the property of their respective owners and do not indicate or imply any affiliation, sponsorship or endorsement of DMP or its products.